



## FUNCTIONAL SAFETY CERTIFICATE

This is to certify that the

***24/924CE Series Miniature Safety Limit Switch***

manufactured by

***Honeywell International Inc.***

315 East Stephenson Street,  
Freeport, Illinois,  
IL61032,  
USA.

has been assessed by Sira Certification Service with reference to the Hardware and Systematic Safety Integrity and found to meet the requirements of

**IEC 61508-2:2010  
Routes 1<sub>H</sub> & 1<sub>S</sub>  
Systematic Capability (SC3)**

as an element/subsystem suitable for use in safety related systems performing safety functions up to and including

**SIL 2 capable with HFT=0 (1oo1)\*  
SIL 3 capable with HFT=1 (1oo2)\***

When used in accordance with the scope and conditions of this certificate.

\*This certificate does not waive the need for further functional safety verification to establish the achieved Safety Integrity Level (SIL) of the safety related system

Certification Manager:

  
Mr W Thomas

Initial Certification: 25/03/2010  
This certificate issued: 22/04/2020  
Renewal date: 15/06/2025

This certificate may only be reproduced in its entirety, without any change.



## Product description and scope of certification

The 24CE series and 924CE series are very small limit switches intended for small doors and apertures in industrial machinery. The 24CE series is CE certified and fitted with European approved cable; the 924CE series is CE certified and fitted with UL recognized cable. The switch is fitted with up to 2 pairs of switching contacts (available in several configurations). The switch is actuated via a plunger and is enclosed in a painted die cast enclosure.



**Figure 1:** Final Assembly of the 24/924CE Series Miniature Safety Limit Switch.

## Use in safety function(s)

The functionality of the certified device that has been assessed for use by safety functions is to open the normally closed (NC) switch contacts on actuation of the plunger.

The user should note the number of cycles for which the safety-related data is valid.

## Certified Data in support of use in safety functions

The assessment has been carried out with reference to IEC61508:2010 for Hardware Safety Integrity using the Route 1<sub>H</sub> approach and the *Conformity Assessment of Safety-related Systems* (CASS) methodology for Systematic Safety Integrity using the Route 1<sub>s</sub> approach.

Based on the documents submitted by Honeywell Control Systems Ltd, the Failure Mode and Effect analysis (FMEA) of the 24/924CE Series Miniature Safety Limit Switch has verified the documents as evidence of conformity to IEC61508-2:2010 in respect of hardware and systematic safety integrity. Component failure rates have been sourced using Item software reliability package and RIAC automated data book. The table below summarizes the FMEA assessment.



## Sira Certification Service CSA Group UK

Unit 6 Hawarden Industrial Park,  
Hawarden, CH5 3US, United Kingdom.  
Tel: +44 (0) 1244 670900  
Email: [ukinfo@csagroup.org](mailto:ukinfo@csagroup.org)  
Web: [www.csagroupuk.org](http://www.csagroupuk.org)

**Table 1;** FMEA results of the 24/924CE Series Miniature Safety Limit Switch

<b>Safety Function:</b> The functionality of the certified device that has been assessed for use by safety functions is to open the normally closed (NC) switch contacts on actuation of the plunger.				
The user should note the number of cycles for which the safety-related data is valid.				
<b>Summary of IEC 61508-2 Clauses 7.4.2 and 7.4.4</b>		24/924CE Series Miniature Safety Limit Switch		<b>Verdict</b>
Architectural constraints & Type of product A/B		<b>HFT=0</b>	<b>HFT=1</b>	<b>Type A</b>
Safe Failure Fraction (SFF)		<b>85%</b>	<b>85%</b>	<b>HFT=0 SIL 2</b> <b>HFT=1 SIL 3</b>
Random hardware failures: [h <sup>-1</sup> ]	$\lambda_{DD}$ $\lambda_{DU}$	0.00E+00 2.15E-08	0.00E+00 2.15E-09	
Random hardware failures: [h <sup>-1</sup> ]	$\lambda_{SD}$ $\lambda_{SU}$	0.00E+00 1.24E-07	0.00E+00 1.25E-08	
Diagnostic coverage (DC)		0%	0%	
PFD @ PTI = 8760Hrs MTTR = 8 Hrs		<b>9.42E-05</b>	<b>9.43E-06</b>	
Probability of Dangerous failure (High Demand - PFH) [h <sup>-1</sup> ]		2.15E-08	2.15E-09	
Risk Reduction Factor (RRF)		10620	106001	
Hardware safety integrity compliance		Route 1 <sub>H</sub>		
Systematic safety integrity compliance		See report R70017229C (Route 1 <sub>s</sub> )		
Systematic Capability		<b>SC3</b>		
Hardware safety integrity achieved		<b>SIL 2 achieved with HFT=0. SIL 3 achieved with HFT=1.</b>		

**Note 1:** The failure data:

- 1) Failure rates stated in the above tables are in units of failures per hour
- 2) The PFD<sub>AVG</sub> figure shown is for illustration only assuming a proof test interval of 8760 hours and MTTR of 8 hours. Refer to IEC 61508-6 for guidance on PFD<sub>AVG</sub> calculations from the failure data.
- 3) The failure rates do not include no parts failures.

**Table 2: Conditions for maintaining safety integrity capability**

1	Product identification:	24/924CE Series Miniature Safety Limit Switch.
2	Functional specification:	The functionality of the certified device that has been assessed for use by safety functions is to open the normally closed (NC) switch contacts on actuation of the plunger.  The user should note the number of cycles for which the safety-related data is valid.
3-5	Random hardware failure rates:	Refer to table 1 above.
6	Environment limits:	Temperature range:



		0 to +70°C operational (24CE Series) 0 to +105°C operational (924CE Series)
7	Lifetime/replacement limits:	Mechanical endurance: Sira TA 09003/02 Electrical endurance: Sira TA 09013/02
8	Proof Test requirements:	Refer to Installation instructions (24/924CE series), document number XP 4047.
9	Maintenance requirements:	Refer to Installation instructions (24/924CE series), document number XP 4047.
10	Diagnostic coverage:	0%, no diagnostics are available.
11	Diagnostic test interval:	No diagnostic testing is available.
12	Repair constraints:	Refer to Installation instructions (24/924CE series), document number XP 4047.
13	Safe Failure Fraction:	85%.
14	Hardware fault tolerance (HFT):	HFT=0 is SIL2. HFT=1 is SIL3.
15	Highest SIL (architecture/type A/B):	SIL3 with HFT=1, Type A product.
16	Systematic failure constraints:	Refer to Installation instructions (24/924CE series), document number XP 4047.
17	Evidence of similar conditions in previous use:	Not applicable – product is proven by design type.
18	Evidence supporting the application under different conditions of use:	Not applicable – product is proven by design type.
19	Evidence of period of operational use:	Not applicable – product is proven by design type.
20	Statement of restrictions on functionality:	Not applicable – product is proven by design type.
21	Systematic capability:	SC3.
22	Systematic fault avoidance measures:	See report R70017229C.
23	Systematic fault tolerance measures:	See report R56A19357A.
24	Validation records:	See reports R70017229C and R56A19357A.

## Management of functional safety

The assessment has demonstrated that the product is supported by an appropriate functional safety management system that meets the relevant requirements of IEC 61508-1:2010 clause 6, see report R70017229C.

## Identification of certified equipment

A full list of certified equipment documents are defined below:

Document no.	Rev	Date	Document description
ASSY-CE-272, type E	8	28/02/2008	Engineering drawing for switch, incl. variants
24 ce series chart 1, type I	16	17/04/2015	Installation drawing for switch, incl. variants
24 ce series chart 2, type I	10	17/04/2015	Installation drawing for switch, incl. variants
24 ce series chart 3, type I	4	09/10/2014	Installation drawing for switch, incl. variants
924 ce series chart 1, type I	17	05/06/2006	Installation drawing for switch, incl. variants
924 ce series chart 2, type I	9	27/02/2008	Installation drawing for switch, incl. variants
XP 4047	7	N/A	Installation Instructions (24/924CE Series)

## Conditions of Certification

The validity of the certified base data is conditional on the manufacturer complying with the following conditions:

1. The manufacturer shall analyse failure data from returned products on an on-going basis. Sira Certification Service shall be informed in the event of any indication that the actual failure rates



## Sira Certification Service CSA Group UK

Unit 6 Hawarden Industrial Park,  
Hawarden, CH5 3US, United Kingdom.  
Tel: +44 (0) 1244 670900  
Email: ukinfo@csagroup.org  
Web: www.csagroupuk.org

are worse than the certified failure rates. (A process to rate the validity of field data should be used. To this end, the manufacturer should co-operate with users to operate a formal field-experience feedback programme).

2. Sira shall be notified in advance (with an impact analysis report) before any modifications to the certified equipment or the functional safety information in the user documentation is carried out. Sira may need to perform a re-assessment if modifications are judged to affect the product's functional safety certified herein.
3. On-going lifecycle activities associated with this product (e.g., modifications, corrective actions, field failure analysis) shall be subject to surveillance by Sira in accordance with 'Regulations Applicable to the Holders of Sira Certificates'.

### Conditions of Safe Use

The validity of the certified base data in any specific user application is conditional on the user complying with the following conditions:

1. Selection of this equipment for use in safety functions and the installation, configuration, overall validation, maintenance and repair shall only be carried out by competent personnel, observing the manufacturer's conditions and recommendations in the user documentation.
2. All information associated with any field failures of this product should be collected under a dependability management process (e.g., IEC 60300-3-2) and reported to the manufacturer.
3. A proof test interval of 1 year.

### General Conditions and Notes

1. This certificate is based upon a functional safety assessment of the product described in Sira Test & Certification Assessment Reports R70017229B, R70017229C and R56A19357A.
2. If the certified product is found not to comply, Sira Certification Service should be notified immediately at the address shown on this certificate.
3. The use of this Certificate and the Sira Certification Mark that can be applied to the product or used in publicity material are subject to the 'Regulations Applicable to the Holders of Sira Certificates' and 'Supplementary Regulations Specific to Functional Safety Certification'.
4. This document remains the property of Sira and shall be returned when requested by the issuer.
5. No part of the Functional safety related aspects stated in the installation instructions shall be changed without approval of the certification body.
6. This certificate will remain valid subject to completion of two surveillance audits within the five year certification cycle, and upon receipt of acceptable response to any findings raised during this period. This certificate can be withdrawn if the manufacturer no longer satisfies scheme requirements.

### Certificate History

Issue	Date	Project No.	Comment
02	03/07/2015	70017229	Revision 2 of this certificate to support recertification of the 24/924CE Series Miniature Safety Limit Switch to IEC61508:2010.
03	23/12/2019	80023138	Certificate updated to include new additional manufacturing location.
04	22/04/2020	80036705	Certificate re-issued following successful recertification. Also includes removal of additional manufacturing location.

